



An  
Employee  
Owned  
Company

# 30-Gallon Air Compressor/ Generator Combinations

*Two Stage — Gasoline*



AG2-SH13-30M

*The 30-gallon two stage air compressor/generators tie two units into one for optimal power remodelers, contractors and DIYers appreciate.*

#### COMPRESSOR PUMP

- Cast iron compressor pump
- Splash lubricated
- Stainless-steel braided discharge hose
- Large canister intake filter
- Oil level sight indicator

#### GENERATOR

- Brushless alternator
- Total harmonic distortion (THD) less than 6%
- 100% copper windings
- (2) NEMA 5-20R 120V, 20A and (1) NEMA L6-20R 240V, 20A receptacles

#### FRAME

- Powder coated ASME receiver tank
- 3/16-inch base plate to reduce vibration
- Powder coated two-piece belt guard

#### COMPONENTS

- Regulator and two gauges for tank and outlet pressure
- Manual drain valves for proper maintenance
- 16½-inch fly wheel
- Quality pilot valve unloader

#### LIMITED WARRANTY

- 3 year engine

#### CERTIFICATION

- ASME Boiler and Pressure Vessel Code – UM



# 30-Gallon

## Air Compressor/Generator Combinations – Two Stage – Gasoline

MODEL NUMBER	CFM @ PSI	CFM @ PSI*	MAX. AC OUTPUT	ALTERNATOR WATTAGE		DISPLACEMENT/ENGINE	DIMENSIONS (LxWxH)	SHIP WT.	NET WT.
				CONT. WITH COMP. ON-LOAD	CONT. WITH COMP. OFF-LOAD				
AG2-SH13-30M	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	389cc Honda GX390 OHV+	40x24.5x45in.	550 lb.	450 lb.
AG2-SH13-30ME^	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	389cc Honda GX390 OHV+	40x24.5x45in.	557 lb.	457 lb.
AG2-SK14-30M	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	429cc Kohler CH440 OHV	40x24.5x45in.	550 lb.	450 lb.
AG2-SK14-30ME^	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	429cc Kohler CH440 OHV	40x24.5x45in.	557 lb.	457 lb.
AG2-SM14-30M	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	420cc Mi-T-M OHV	40x24.5x45in.	550 lb.	450 lb.
AG2-SM14-30ME^	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	420cc Mi-T-M OHV	40x24.5x45in.	557 lb.	457 lb.
AG2-SV14-30M	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	408cc Vanguard OHV	40x24.5x45in.	550 lb.	450 lb.
AG2-SV14-30ME^	16.4 @ 90	15.7 @ 175	4000 watts	2300 watts	3500 watts	408cc Vanguard OHV	40x24.5x45in.	557 lb.	457 lb.

Note: All gasoline models sold in California are required to have a CARB compliant engine. Consult factory.

\*Equipped with 150-PSI maximum rated regulator. \*49 state engine. Not for sale in California. ^Equipped with electric start – battery, box and cables not included.

### ACCESSORIES:

PART NUMBER	DESCRIPTION	FITS MODELS
70-0358	Engine oil drain extension – 14-inch flexible drain hose makes oil changes clean and easy	All models
AW-6000-1002	Equipment cover – Keeps your equipment clean, dry and looking like new	All models

### OPTIONS:

PART NUMBER	DESCRIPTION	FITS MODELS
AX-0016	Battery, battery tray, box and 2-foot of cables – Attaches to engine side of unit	Electric start models
AX-0063	Lifting hook – For easier portability	All models
AX-0068	Idle down – When activated it automatically throttles down engine to conserve fuel	Honda engine models
AX-0070	Battery tray, box and 2-foot of cables – Attaches to engine side of unit	Electric start models
AX-0075	Idle down – When activated it automatically throttles down engine to conserve fuel	Mi-T-M engine models
AX-0083	Idle down – When activated it automatically throttles down engine to conserve fuel	Vanguard engine models
IX-0001	Vibration isolator pads – Isolators protect the unit from vibration during use. Recommended for models mounted in service truck applications.	All models
IX-0055	Remote start/choke – 7-foot wire extension for key switch	AG2-SH13-30ME
IX-0059	Remote start/choke, sealed cable – 7-foot wire extension for key switch	AG2-SH13-30ME
IX-0060	Remote start/choke, sealed cable – 7-foot wire extension for key switch	AG2-SV14-30ME
IX-0067	Remote start/choke, sealed cable – 7-foot wire extension for key switch	AG2-SM14-30ME



NEMA 5-20R  
125V



NEMA L6-20R  
240V

**WARNING:** Cancer and Reproductive Harm - [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov).